

E Series Resistor and Capacitor Values

E3 Error 40%	E6 Error 20%	E12 Error 10%	E24 Error 5%1%	
10	10	10	10	
			11	
		12	12	
			13	
	15	15	15	
			16	
		18	18	
			20	
	22	22	22	22
				24
27			27	
			30	
33		33	33	
			36	
		39	39	
			43	
47		47	47	47
				51
	56		56	
			62	
	68	68	68	
			75	
		82	82	
			91	

Resistor Values : There is a lot of E12 series for being sold.

There is also 5% 1% by E12 series.

Capacitor Values : There is a lot of E6 series for being sold.

There is also 10% 5% by E6 series.